

Leakage Clamp Meters

MODEL **2413F**

- Extra wide transformer jaws are best suited for clamping on all three or four wires (3phases) together for leakage current measurement.
- Frequency filter switch to eliminate the effect of harmonics.
- Peak hold function.
- Analogue output terminal.

Φ68	MAX AC1000A	Resolution 0.1mA	OUT PUT
PEAK 10/100ms	Filter		



CE

AC A (50/60Hz)	200mA/2/20/200A/1000A ±1.5%rdg±2dgt (200mA/2/20A) ±2%rdg±2dgt (200A 0~500A) ±5.5%rdg (501~1000A)
AC A (WIDE)	200mA/2/20/200/1000A ±1%rdg±2dgt [50/60Hz], ±3%rdg±2dgt [40Hz~1kHz] (200mA/2/20A) ±1.5%rdg±2dgt [50/60Hz], ±3.5%rdg±2dgt [40Hz~1kHz] (200A/0~500A) ±5%rdg [50/60Hz], ±10%rdg [40Hz~1kHz] (501~1000A)
Conductor Size	Ø68mm max.
Effect of External Stray Magnetic Field Ø15mm 100A	10mA AC max.
Frequency Response	40Hz~1kHz
Output	AC/DC 200mV against 2000 count
Withstand Voltage	3700V AC for 1 minute
Applicable Standard	IEC61010-1 CAT.III 300V IEC61010-2-032
Power Source	6F22(9V) × 1 *Continuous measuring time: Approx. 60 hours
Dimensions	250(L) × 130(W) × 50(D)mm
Weight	570g approx.
Accessories	9094(Carrying Case) 6F22 × 1 Instruction Manual
Optional	7073(2WAY Output Cord)