

● Process multimeter

VICTOR 78
3 3/4VICTOR 79
3 3/4

- Process Meter is a handheld, battery-operated tool for measuring electrical parameters. It has all the features of a digital multimeter (besides the feature of RTD and TC), it could also output signals of direct voltage, current, resistance, temperature and frequency as well.
- Auto/manual range switch, Measure value display hold
- The thermocouple high accuracy cold-end can auto offset
- Panel auto calibrated
- The function of auto close backlight and auto power-off
- Large LCD include white LED backlight
- It is easy to operation by user, cabinet and solid adapt to be used at locale

VICTOR 78/79 Process multimeter

Technical data

Measuring function	Range	Measuring range	Resolving power	Accuracy	Remark
DC Voltage	4V	-4.000V~4.000V	1mV	0.2%+4	input impedance: 10MΩ
	40V	-40.00V~40.00V	0.1V	0.2%+4	
	400V	-400.0V~400.0V	0.1V	0.2%+4	
AC Voltage (40Hz~500Hz) (5%~100%RANG)	400mV	0~400.0mV	0.1mV	1%+4	input impedance: 10MΩ <100pF
	4V	0~4.000V	1mV	0.5%+4	
	40V	0~40.00V	0.1V	0.5%+4	
DC Mv Voltage	40mV	-40.00mV~40.00mV	0.01mV	0.5%+6	input impedance:10MΩ
	400mV	-400.0mV~400.0mV	0.1mV	0.2%+4	
	400Ω	0~400.0Ω	0.1Ω	0.2%+4	
OHM	4KΩ	0~4.000 KΩ	1Ω	0.2%+4	Plough voltage:0.4V not including the accuracy of down-lead resistance
	40KΩ	0~40.00KΩ	0.01KΩ	0.2%+4	
	400KΩ	0~400.0KΩ	0.1KΩ	0.2%+4	
4MΩ	4MΩ	0~4.000MΩ	1KΩ	0.2%+4	40MΩ
	40MΩ	0~40.00MΩ	0.01MΩ	1%+4	
	400MΩ	0~400.0MΩ	0.1MΩ	0.2%+4	
DC Current	40mA	-40.00mA~40.00mA	0.01mA	0.2%+4	input impedance: 1Ω
	400mA	-400.0mA~400.0mA	0.1mA	0.5%+4	
	40mA	0~40.00mA	0.01mA	0.5%+4	
AC Current (40Hz~200Hz) (5%~100%RANG)	400mA	0~400.0mA	0.1mA	0.5%+4	input impedance:1Ω
	4000mA	0~4000.0mA	1μA	0.5%+4	
	50Hz	0~50.0Hz	0.01Hz	0.1%+3	
Frequency	500Hz	0~500.0Hz	0.1Hz	0.1%+3	5kHz
	5kHz	0~5.000kHz	1Hz	0.1%+3	
	50kHz	0~50.0kHz	0.01kHz	0.1%+3	
100kHz	100kHz	0~100.0kHz	0.1kHz	0.1%+3	Duty cycle Diode test
	0.1%~99%		0.1%	1%	
	1V		0.001V	10%	
Continuity test	<50ΩBB		0.1Ω		Plough voltage:1.1V-1.5V Current of short circuit: 0.6mA
	R	-40°C~1760°C	1°C	0.5%+3 (<100°C)	
	S	-20°C~1760°C		0.5%+2 (>100°C)	
Thermocouple*	K	-200°C~950°C			Adopt ITS-90 thermometric scale not including the accuracy of RJC error RJC error:±2°C
	E	-200°C~500°C	1°C	0.2%+2 (<-100°C)	
	J	-200°C~700°C		0.5%+1 (>-100°C)	
T	T	-200°C~400°C			PT100-385 thermometric scale,not including the accuracy of down-lead resistance
	N	-200°C~1000°C	1°C	0.5%+1 (400~600°C)	
	B	400°C~1800°C		0.5%+2 (>600°C)	
Thermo resistance*	Pt100	-200°C~700°C	1°C	0.5%+2	PT100-385 thermometric scale,not including the accuracy of down-lead resistance
	Cu50	-50°C~150°C	1°C	0.5%+4	

Output Function

Function	Range	Setting range	Resolving power	Accuracy	Remark
OMH*	400Ω	0~400.0Ω	0.1Ω	0.2%+4	0.1mA current not including the accuracy of down-lead resistance
78DCmV	500mV	-50.00mV~550.00mV	0.1mV	0.5%+6	Max output current: 5mA
79DCmV	100mV	-10.00mV~110.00mV	0.01mV	0.2%+4	Max output current: 5mA
DCV	3V	-0.5000V~5.5000V	1mV	0.2%+4	Max output current: 5mA
	100Hz	1.0Hz~110.0Hz	0.1Hz	0.2%+2	
FREQ	1kHz	0.100kHz~1.100kHz	0.001kHz	0.2%+2	50% Duty cycle
	10kHz	1.0kHz~11.0kHz	0.1kHz	0.2%+2	5Vp-p
Analog transducer XMT	>20mA	0~22.000mA	0.01mA	0.2%+4	Outside power supply 2kV when 20 mA 1kΩ resistance
DCmA	20mA	0~22.000mA	0.01mA	0.2%+4	Outside power supply 15V When 20 mA 400Ω resistance
Thermocouple*	R	-40°C~1760°C	1°C	0.2%+3 (<100°C)	Adopt ITS-90 thermometric scale not including the accuracy of RJC error RJC error:±2°C
	S	-20°C~1760°C		0.5%+2 (>100°C)	
	K	-200°C~1370°C			
	E	-200°C~1000°C	0.1°C	0.5%+20 (<-100°C)	
	J	-200°C~1200°C		0.5%+10 (>-100°C)	
	T	-200°C~400°C			
Thermo resistance*	N	-200°C~1300°C	1°C	0.5%+2 (400~800°C)	PT100-385 thermometric scale:0.1mA not including the accuracy of down-lead resistance
	B	400°C~1800°C		0.5%+2 (>800°C)	
	Pt100	-200°C~850°C	0.1°C	0.2%+6	
	Cu50	-50°C~150°C	0.1°C	0.5%+4	

Note : * only for model 79