



### DT-3353 True RMS 1000A AC Watt Clamp Meter

3353 Professional True RMS 1000A AC Watt Clamp Meter provides accurate Watt, AC Current and Voltage readings regardless of waveforms.

#### Features:

Analysis for Single Phase and Balanced 3 phase system
True RMS Value (Voltage and Current)
Large LCD Display with Backlight
USB interface
4 digits with dual display LCD
MIN / MAX measurement
True power / apparent power / power factor measurement
Data Hold
Auto Ranging
Overflow Indication
Auto Power Off
Manual Data Memory and Read (99 sets)
NCV Detection
2.16" (55mm) Jaw opening

#### Specifications:

Function	Range	Basic Accuracy
AC Voltage	15V/100V/300V/750V	$\pm(1.2\%+5)$
AC Current	40A/100A/400A/1000A	$\pm(2\%+5)$
True Power	0.60kW—750kW	$\pm(3\%+5)$
Apparent Power	0.60kVA—750kVA	$\pm(3\%+5)$
Reactive Power	0.60kVAr—750kVAr	$\pm(4\%+20)$ of 15V/1000A else $\pm(4\%+5)$
Power Factor	0.3-1	$\pm(2\%+20)$
Phase Angle	0°-90°	$\pm 1^\circ$
Frequency	20Hz-200Hz	$\pm(0.5\%+5)$
Energy	1-9999kWh	$\pm(3\%+2)$
Size(HxWxD)	295mm x 100mm x 46mm	
Weight	537g	

#### Accessories:

Test leads, gift box with carrying case and 9V battery, USB Cable, CD Software.

